Data sheet

SIMATIC ET 200SP, ANALOG INPUT MODULE, AI 4XI 2-/4-WIRE STANDARD, PACKING UNIT: 1 PIECE, FITS TO BU-TYPE A0, A1, COLOR CODE CC03, MODULE DIAGNOSIS, 16BIT, +/-0,3%



General information	
Product type designation	Al 4xl 2-/4-wire ST
HW functional status	From FS02
Firmware version	
 FW update possible 	Yes
usable BaseUnits	BU type A0, A1
Color code for module-specific color identification	CC03
plate	
Product function	
● I&M data	Yes; I&M0 to I&M3
 Measuring range scalable 	No
Engineering with	
 STEP 7 TIA Portal configurable/integrated as of 	V14 / -
version	
 STEP 7 configurable/integrated as of version 	V5.6 and higher
 PCS 7 configurable/integrated as of version 	V8.1 SP1
 PROFIBUS as of GSD version/GSD revision 	One GSD file each, Revision 3 and 5 and higher
 PROFINET as of GSD version/GSD revision 	GSDML V2.3
Operating mode	

 Oversampling 	No
• MSI	No
0:0 0 6 6 6 7 8 1	
CiR – Configuration in RUN Reparameterization possible in RUN	Yes
Calibration possible in RUN	No
Supply voltage	
Rated value (DC)	24 V
permissible range, lower limit (DC)	19.2 V
permissible range, upper limit (DC)	28.8 V
Reverse polarity protection	Yes
Input current	
Current consumption, max.	37 mA; without sensor supply
Encoder supply	
24 V encoder supply	
• 24 V	Yes
Short-circuit protection	Yes
Output current, max.	20 mA; max. 50 mA per channel for a duration < 10 s
5 t.p. a.	· '
Power loss	
Power loss, typ.	0.85 W; Without encoder supply voltage
Address area	
Address area Address space per module	
	8 byte; + 1 byte for QI information
Address space per module	8 byte; + 1 byte for QI information
Address space per module • Address space per module, max.	8 byte; + 1 byte for QI information
Address space per module • Address space per module, max. Hardware configuration	8 byte; + 1 byte for QI information Yes
Address space per module • Address space per module, max. Hardware configuration Automatic encoding	
Address space per module • Address space per module, max. Hardware configuration Automatic encoding • Mechanical coding element	
Address space per module • Address space per module, max. Hardware configuration Automatic encoding • Mechanical coding element Selection of BaseUnit for connection variants	Yes
Address space per module • Address space per module, max. Hardware configuration Automatic encoding • Mechanical coding element Selection of BaseUnit for connection variants • 2-wire connection • 4-wire connection	Yes BU type A0, A1
Address space per module • Address space per module, max. Hardware configuration Automatic encoding • Mechanical coding element Selection of BaseUnit for connection variants • 2-wire connection • 4-wire connection Analog inputs	Yes BU type A0, A1 BU type A0, A1
Address space per module • Address space per module, max. Hardware configuration Automatic encoding • Mechanical coding element Selection of BaseUnit for connection variants • 2-wire connection • 4-wire connection Analog inputs Number of analog inputs	Yes BU type A0, A1 BU type A0, A1 4; Differential inputs
Address space per module • Address space per module, max. Hardware configuration Automatic encoding • Mechanical coding element Selection of BaseUnit for connection variants • 2-wire connection • 4-wire connection Analog inputs	Yes BU type A0, A1 BU type A0, A1
Address space per module • Address space per module, max. Hardware configuration Automatic encoding • Mechanical coding element Selection of BaseUnit for connection variants • 2-wire connection • 4-wire connection Analog inputs Number of analog inputs permissible input current for current input (destruction	Yes BU type A0, A1 BU type A0, A1 4; Differential inputs
Address space per module • Address space per module, max. Hardware configuration Automatic encoding • Mechanical coding element Selection of BaseUnit for connection variants • 2-wire connection • 4-wire connection Analog inputs Number of analog inputs permissible input current for current input (destruction limit), max.	Yes BU type A0, A1 BU type A0, A1 4; Differential inputs 50 mA Sum of the basic conversion times and additional processing
Address space per module • Address space per module, max. Hardware configuration Automatic encoding • Mechanical coding element Selection of BaseUnit for connection variants • 2-wire connection • 4-wire connection Analog inputs Number of analog inputs permissible input current for current input (destruction limit), max. Cycle time (all channels), min.	Yes BU type A0, A1 BU type A0, A1 4; Differential inputs 50 mA Sum of the basic conversion times and additional processing
Address space per module • Address space per module, max. Hardware configuration Automatic encoding • Mechanical coding element Selection of BaseUnit for connection variants • 2-wire connection • 4-wire connection Analog inputs Number of analog inputs permissible input current for current input (destruction limit), max. Cycle time (all channels), min.	Yes BU type A0, A1 BU type A0, A1 4; Differential inputs 50 mA Sum of the basic conversion times and additional processing times (depending on the parameterization of the active channels)
Address space per module • Address space per module, max. Hardware configuration Automatic encoding • Mechanical coding element Selection of BaseUnit for connection variants • 2-wire connection • 4-wire connection Analog inputs Number of analog inputs permissible input current for current input (destruction limit), max. Cycle time (all channels), min. Input ranges (rated values), currents • 0 to 20 mA	Yes BU type A0, A1 BU type A0, A1 4; Differential inputs 50 mA Sum of the basic conversion times and additional processing times (depending on the parameterization of the active channels) Yes; 16 bit incl. sign
Address space per module Address space per module, max. Hardware configuration Automatic encoding Mechanical coding element Selection of BaseUnit for connection variants 2-wire connection 4-wire connection Analog inputs Number of analog inputs permissible input current for current input (destruction limit), max. Cycle time (all channels), min. Input ranges (rated values), currents 0 to 20 mA Input resistance (0 to 20 mA)	Yes BU type A0, A1 BU type A0, A1 4; Differential inputs 50 mA Sum of the basic conversion times and additional processing times (depending on the parameterization of the active channels) Yes; 16 bit incl. sign 100Ω ; + approx. 0.7 V diode forward voltage in 2-wire operation

• 4 mA to 20 mA	Yes; 15 bit
 Input resistance (4 mA to 20 mA) 	100 $\Omega;$ + approx. 0.7 V diode forward voltage in 2-wire operation
Cable length	
• shielded, max.	1 000 m

Analog value generation for the inputs	
Measurement principle	integrating (Sigma-Delta)
Integration and conversion time/resolution per channel	
 Resolution with overrange (bit including sign), 	16 bit
max.	
 Integration time, parameterizable 	Yes
 Interference voltage suppression for 	16.6 / 50 / 60 Hz
interference frequency f1 in Hz	
 Conversion time (per channel) 	180 / 60 / 50 ms
Smoothing of measured values	
Number of smoothing levels	4; None; 4/8/16 times
parameterizable	Yes

Encoder		
	Connection of signal encoders	
	for voltage measurement	No
	• for current measurement as 2-wire transducer	Yes
	— Burden of 2-wire transmitter, max.	650 Ω
	• for current measurement as 4-wire transducer	Yes

Errors/accuracies	
Linearity error (relative to input range), (+/-)	0.01 %
Temperature error (relative to input range), (+/-)	0.005 %/K
Crosstalk between the inputs, min.	50 dB; Applies to up to ±5 V overvoltage in other channels
Repeat accuracy in steady state at 25 °C (relative to input range), (+/-)	0.05 %
Operational error limit in overall temperature range	
 Current, relative to input range, (+/-) 	0.5 %
Basic error limit (operational limit at 25 °C)	
 Current, relative to input range, (+/-) 	0.3 %
Interference voltage suppression for $f = n \times (f1 +/- 1 \%)$,	f1 = interference frequency
 Series mode interference (peak value of interference < rated value of input range), min. 	70 dB
 Common mode voltage, max. 	10 V
Common mode interference, min.	90 dB

Isochronous mode Isochronous operation (application synchronized up to terminal)	No
Interrupts/diagnostics/status information	

Diagnostics function	Yes
Alarms	
Diagnostic alarm	Yes
Limit value alarm	No
Diagnostic messages	
Monitoring the supply voltage	Yes
Wire-break	Yes; at 4 to 20 mA
Short-circuit	Yes; 2-wire mode: Short-circuit of the encoder supply to ground or of an input to the encoder supply
Group error	Yes
Overflow/underflow	Yes
Diagnostics indication LED	
 Monitoring of the supply voltage (PWR-LED) 	Yes; Green LED
Channel status display	Yes; Green LED
• for channel diagnostics	No
• for module diagnostics	Yes; Green/red LED
Potential separation	
Potential separation channels	
• between the channels	Yes; channel group-specific between 2-wire current input group and 4-wire voltage input group
 between the channels and backplane bus 	Yes
 between the channels and the power supply of the electronics 	Yes; only for 4-wire transducer
Isolation	
Isolation tested with	707 V DC (type test)
Ambient conditions	
Ambient temperature during operation	
horizontal installation, min.	-30 °C
horizontal installation, max.	60 °C
 vertical installation, min. 	-30 °C
 vertical installation, max. 	50 °C
Altitude during operation relating to sea level	
• Installation altitude above sea level, max.	5 000 m; Restrictions for installation altitudes > 2 000 m, see manual
Dimensions	
Width	15 mm
Height	73 mm
Depth	58 mm
Weights	
Weight, approx.	31 g

last modified: 12/14/2019