



DEEP RINGO LED 92733 W

202 272 811 922 W

AVAILABLE IN



BLACK 202 272 811 922 B

FLEMISH BRONZE 202 272 811 922 FBR

FLEMISH GOLD 202 272 811 922 FG

GOLD COLORED 202 272 811 922 GC

WHITE 202 272 811 922 W



[View on website](#)

General info

LOCATION	interior
INSTALLATION	Ceiling Recessed
CUTOUT SHAPE/SIZE (MM)	round - 76
RECESSED DEPTH (MM)	90
THICKNESS OF MOUNTING SURFACE (MM)	min.5
INGRESS PROTECTION	IP43/20
WEIGHT (KG)	0.2
ADJUSTABILITY	non adjustable
INFORMATION	REFLECTOR FL-33° EXCL.LED POWER SUPPLY 350-500mA-DC

Electrical info

CLASS	III
ENERGY CLASS	E

Lightsource info

Lightsource Name	LED
Lightsource	LED array 7,1-10,4W / CRI>90 (R9: 60) / 2700K / 779-1083lm
TM-30 Values	Rf: 89 / Rg: 100
SDCM	SDCM2
Riskgroup	RG1
LM80	L90B10 > 50000
LED Technics (light source)	1083lm // 10,4W // 105lm/W
LED Technics (luminaire)	799lm // 12W // 67lm/W

Requirements

LED POWER SUPPLY 350 / 500mA-DC DIM

For detailed installation instructions, please consult the manual: [202_272_811_XXX_HAND.pdf](#)

DEEP RINGO LED 92733 W

202 272 811 922 W

CEILING COMPATIBILITY

Ceiling Type	Mounting Kit
 System ceiling	-
 Plasterboard	-
 Stucanet	-
 Wood	-
 Concrete	-
 Concrete + plaster	-
 Lintel + plaster	-
 Hollow-core slab	-
 Hollow-core slab + plaster	-
 Stretched ceiling	-


DEEP RINGO LED 92733 W

202 272 811 922 W

FINISH YOUR SPECIFICATION


LED power supplies

#




300 48 350 ED1 LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM1

1

☐



300 48 350 ED5 LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5

1

☐



300 48 350 MDL LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W MDL

1

☐



300 48 350 WDL LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W WDL

1

☐



300 48 500 ED1 LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM1

1

☐



300 48 500 ED5 LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5

1

☐



300 48 500 MDL LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W MDL

1

☐


300 48 500 WDL LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W WDL

1

☐



300 90 61 LED POWER SUPPLY MULTI-POWER DIM6

1->2 / 1->2

☐

DEEP RINGO LED 92733 W


202 272 811 922 W



300 90 63

LED POWER SUPPLY MULTI-POWER DIM9


1->3(3) / 1->3(3)



300 90 64

LED POWER SUPPLY MULTI-POWER DIM7


1->2(1) / 1->2(1)



300 90 67

LED POWER CONVERTER 24V-DC TO MULTI CURRENT 48W DIM9


1->2



300 90 68

LED POWER SUPPLY MULTI-POWER DIM5


1->2(1) / 1->2(1)



300 90 69

LED POWER SUPPLY MULTI-POWER HV DIM9


2->5(5) / 1->5(3)



300 90 124

LED POWER SUPPLY MULTI-POWER DIM7


1->2(1) / 1(1)



300 90 125

LED POWER SUPPLY MULTI-POWER MINI DIM5


1->2(1) / 1(1)



300 90 135

LED POWER SUPPLY MULTI-POWER HV


3->3 / 2->3



21012 004W

LED POWER SUPPLY MULTI-POWER WDL

1->3(3) / 1->3(3)



21012 005W







LED POWER SUPPLY MULTI-POWER COMPACT WDL

1->2 / 1->2



DEEP RINGO LED 92733 W

202 272 811 922 W

	21012 0258	LED POWER SUPPLY MULTI POWER 200-350 / 10W DIM8	1	☐
	21012 0278	LED POWER SUPPLY MULTI POWER 500-700 / 20W DIM8	1	☐
	21012 0288	LED POWER SUPPLY MULTI POWER 500-700 / 36W DIM8	2->2	☐
	21012 0298	LED POWER SUPPLY MULTI POWER 250-900 / 20W DIM8	2/1	☐
	21032 0295	LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5	1	☐
	21032 0305	LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5	1	☐

Notes: