



DEEP RINGO LED 93033 W

202 272 811 932 W

AVAILABLE IN



BLACK 202 272 811 932 B

FLEMISH BRONZE 202 272 811 932 FBR

FLEMISH GOLD 202 272 811 932 FG

GOLD COLORED 202 272 811 932 GC

WHITE 202 272 811 932 W



[View on website](#)

General info

LOCATION	interior
INSTALLATION	Ceiling Recessed
CUTOUT SHAPE/SIZE (MM)	round - 76
RECESSED DEPTH (MM)	90
THICKNESS OF MOUNTING SURFACE (MM)	min.5
INGRESS PROTECTION	IP43/20
WEIGHT (KG)	0.2
ADJUSTABILITY	non adjustable
INFORMATION	REFLECTOR FL-33° EXCL.LED POWER SUPPLY 350-500mA-DC

Electrical info

CLASS	III
ENERGY CLASS	E

Lightsource info

Lightsource Name	LED
Lightsource	LED array 7,1-10,4W / CRI>90 (R9: 52) / 3000K / 812-1128lm
TM-30 Values	Rf: 90 / Rg: 99
SDCM	SDCM2
Riskgroup	RG1
LM80	L90B10 > 50000
LED Technics (light source)	1128lm // 10,4W // 109lm/W
LED Technics (luminaire)	832lm // 12W // 70lm/W

Requirements

LED POWER SUPPLY 350 / 500mA-DC DIM

For detailed installation instructions, please consult the manual: [202_272_811_XXX_HAND.pdf](#)

DEEP RINGO LED 93033 W

202 272 811 932 W

CEILING COMPATIBILITY

Ceiling Type	Mounting Kit
 System ceiling	-
 Plasterboard	-
 Stucanet	-
 Wood	-
 Concrete	-
 Concrete + plaster	-
 Lintel + plaster	-
 Hollow-core slab	-
 Hollow-core slab + plaster	-
 Stretched ceiling	-


DEEP RINGO LED 93033 W

202 272 811 932 W

FINISH YOUR SPECIFICATION


LED power supplies

#




300 48 350 ED1 LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM1

1

☐



300 48 350 ED5 LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5

1

☐



300 48 350 MDL LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W MDL

1

☐



300 48 350 WDL LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W WDL

1

☐



300 48 500 ED1 LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM1

1

☐



300 48 500 ED5 LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5

1

☐



300 48 500 MDL LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W MDL

1

☐


300 48 500 WDL LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W WDL

1

☐












300 90 61 LED POWER SUPPLY MULTI-POWER DIM6

1->2 / 1->2

☐







DEEP RINGO LED 93033 W

202 272 811 932 W

	300 90 63	LED POWER SUPPLY MULTI-POWER DIM9	1->3(3) / 1->3(3) ☐
	300 90 64	LED POWER SUPPLY MULTI-POWER DIM7	1->2(1) / 1->2(1) ☐
	300 90 67	LED POWER CONVERTER 24V-DC TO MULTI CURRENT 48W DIM9	1->2 ☐
	300 90 68	LED POWER SUPPLY MULTI-POWER DIM5	1->2(1) / 1->2(1) ☐
	300 90 69	LED POWER SUPPLY MULTI-POWER HV DIM9	2->5(5) / 1->5(3) ☐
	300 90 124	LED POWER SUPPLY MULTI-POWER DIM7	1->2(1) / 1(1) ☐
	300 90 125	LED POWER SUPPLY MULTI-POWER MINI DIM5	1->2(1) / 1(1) ☐
	300 90 135	LED POWER SUPPLY MULTI-POWER HV	3->3 / 2->3 ☐
	21012 004W	LED POWER SUPPLY MULTI-POWER WDL	1->3(3) / 1->3(3) ☐
	21012 005W	LED POWER SUPPLY MULTI-POWER COMPACT WDL	1->2 / 1->2 ☐

DEEP RINGO LED 93033 W

202 272 811 932 W

	21012 0258	LED POWER SUPPLY MULTI POWER 200-350 / 10W DIM8	1	☐
	21012 0278	LED POWER SUPPLY MULTI POWER 500-700 / 20W DIM8	1	☐
	21012 0288	LED POWER SUPPLY MULTI POWER 500-700 / 36W DIM8	2->2	☐
	21012 0298	LED POWER SUPPLY MULTI POWER 250-900 / 20W DIM8	2/1	☐
	21032 0295	LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5	1	☐
	21032 0305	LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5	1	☐

Notes: